



PRODUCT INFORMATION



Q-PEDAL Foot Operated Lighting Controller



* *4 x 2300W Power Handling* *



- Foot operated lighting controller
- Robust extruded aluminium case
 - 4 x 2300W 230V output
 - Four Channel Sound Chaser
 - "FLOOD" & "BLACKOUT"
 - Individual Channel Indication
 - 2 x EVF321CAD Output Sockets
 - Interference free switching
- Internal microphone & Line input for audio trigger
- Ideal for PAR CANS or the NJD QUARTET 300



Q-PEDAL TECHNICAL SPECIFICATION

Audio input sensitivity : 1.5V rms to 50V
Audio input impedance : 33k Ohms Audio
input connector : 6.35mm Mono Jack Output
connectors : 2 x EVF321CAD sockets
Output plugs required: 2 x EVF321BA (Not
Supplied)
Output : 10A per channel
Power requirements : 230V V AC 5VA
Dimensions : 405mm x 201mm x 58mm
Weight : 3.1kg

NOTE: POWER SUPPLY REQUIREMENTS

Whilst this product is capable of controlling loads of up to 10A per channel (40A total), The power available through a standard 13A mains plug is limited by the 13A fuse. If the Q-Pedal is connected via a standard 13A plug then it is necessary to reduce the load to 3.25A per channel which is equivalent to lamp wattage of **4 x 750w per channel (3000w Total)**.

EVF "Ready Made" power leads for the Q-Pedal are also available in various lengths

SEE OUR WEB SITE FOR MORE DETAILS: www.premier-solutions.biz